Instruction for Update and Activate AUTEK IKEY820 Key Programmer

1 What you need

- 1) AUTEK IKEY 820 key programmer
- 2) PC with Win10/Win8/Win7/XP
- 3) USB cable

2 Install update tool on your PC

If the update tool "AUTEK IKEY 820 Update Tool V1.2 is already installed on your PC before, just skip this chapter. If not, you need to install it. If you do not have the setup file, please ask your distributor for it.



(a)

🌄 Autek Ikey 820 Update Tool V1.2 Setup.exe

Figure 2.1 (a) The Update Tool short icon,

(b) (b)setup file of the update tool

Double click the setup file to start installing the update tool



Figure 2.1 update tool setup start window



Figure 2.2 update tool setup finish window

Click "Next" until the finish window, and click finish button to end the install program. There will be a shortcut icon on the desktop, see Figure 2(a). AUTEK IKEY 820 Update Tool contains three parts including UPDATE, ACTIVATE and MESSAGE from top to bottom.

	UPDATE SOFTW	ARE	
SN:	DISK:	~	UPDATE
	ACTIVATE TOK	ENS	
REQ CODE:			ACTIVATE
ANS CODE:			
DI	FASE MAKE SURE YOUR PO	IS ON INTERNET	

Figure 2.3 AUTEK IKEY 820 Update Tool window

3 Update

Take the following steps to update AUTEK IKEY 820 device:

- 1) Connect device to PC through USB cable;
- Open AUTEK IKEY 820 Update Tool in your PC that needs to be on internet;
- 3) Select the device in list and input the SN (usually completed automatically);
- 4) Click UPDATE button to start updating, wait until the updating completed.

There is something you need to notice in each step.

- 1) The device should display "USB SD DISK MODE" when connected to PC through USB cable, if not, please unplug the USB cable and plug again. Do not unplug the USB cable or exit from USB SD DISK MODE.
- 2) If AUTEK IKEY 820 Update Tool is not installed, please install it first, see detail in chapter 2.
- 3) The DISK and SN should display automatically if the device is connected to PC. If the DISK has no device to select, please unplug the USB cable and plug again. If the DISK has been selected, but SN is empty, please unplug the USB cable and plug again. If it's still the same, please input SN yourself. The SN should start with "A-".
- 4) It may take several minutes to update, it depends on the speed of your internet.

If there is any problem, it will display on message area, check according to the message and try again.

Here are the pages for updating. The SN is just an example, you should use your own SN.

	UPDA	ATE SOFTWARE		
SN: A-62000002	DISK:	I: AUTEK	~	UPDATE
	ACT	IVATE TOKENS		
REQ CODE:				ACTIVATE
ANS CODE:				
DIT	ASE MAKE SUP	E VOUR PC IS ON	INTERNET	

Figure 3.1 check SN and DISK before update

	UPDATE SOFTWARE	
SN: A-62000002	DISK: I: AUTEK	~ UPDATE
	ACTIVATE TOKENS	
REQ CODE:		ACTIVATE
ANS CODE:		
	UPDATING	

Figure 3.2 wait until update successfully

Autek Ikey 820 Upda	ate Tool V1.2	X
SN: A-62000002	UPDATE SOFTWARE DISK: I: AUTEK ~	UPDATE
REQ CODE:	ACTIVATE TOKENS	ACTIVATE
ANS CODE:	SUCCESS	

Figure 3.3 Update successfully

4 Activate

Activation means add tokens to your device. If your device runs out of tokens or you want to increase the number of tokens, you can use AUTEK IKEY 820 Update Tool to increase tokens.

Take the following steps to activate AUTEK IKEY 820 device:

- 1) Supply power to the AUTEK IKEY 820 device through USB/12V DC adapter/OBD.
- Go to the ACTIVATE menu, you will see a page with steps to activate your device and the REQ CODE which is need in AUTEK IKEY 820 Update Tool to get the ANS CODE.
- 3) Open AUTEK IKEY 820 Update Tool in your PC.
- 4) Input the REQ CODE to the AUTEK IKEY 820 Update Tool and click ACTIVATE button, then you will get the ANS CODE
- 5) Press OK button on the device and there display the page to input ANS CODE.

- 6) Input the ANS CODE you get in the AUTEK IKEY 820 Update Tool. There are two different
- 7) Press OK button and the page will show the result, SUCCESS or FAILED.
- 8) You can check your tokens in the ABOUT menu if you activate your device successfully.

Here are the pictures to activate the device. All the SN $_{\smallsetminus}$ REQ CODE and ANS CODE are examples, just ignore them.



Figure 4.1 Select the ACTIVATE menu



Figure 4.2 The ACTIVATE page

Autek Ikey	820 Update Tool V1.2	X
	UPDATE SOFTWARE	
SN:	DISK: ~	UPDATE
	ACTIVATE TOKENS	
REQ CODE:	9FCC-E388-CA55-4737-A831-8243-6798-3359	ACTIVATE
ANS CODE:]
	PLEASE MAKE SURE YOUR PC IS ON INTERNET	



Autek Ikey	820 Update Tool V1.2	x
	UPDATE SOFTWARE	
SN:	DISK:	UPDATE
	ACTIVATE TOKENS	
REQ CODE:	9FCC-E388-CA55-4737-A831-8243-6798-3359	ACTIVATE
ANS CODE:	0F 5A 30 7E 89 86 D6 47]
	SUCCESS	

Figure 4.4 Get the ANS CODE



Figure 4.5 Input the ANS CODE



Figure 4.6 Confirm the ANS CODE you input

0.100555	
SUCCEED	
	OK

Figure 4.7 SUCCEED means activate successfully

SN:A-62000002		
HW: V3.1		
SW: V2.0.5		
UI: V1.1.4		
TOKENS:200		
BATTERY:4.35V		
ESC		

Figure 4.8 Check the tokens in ABOUT page